





Datasheet SOM-1

Reference Sine Oscillator Module for LIA-BV-150/LIA-MV-200 Series



Features	<ul style="list-style-type: none"> • Sine Wave Output from 5 Hz to 130 kHz • Adjustable Frequency and Amplitude • PLL for Synchronization to External Reference • Plug-In Module for Series LIA-BV(D)-150/LIA-MV(D)-200 Lock-In Amplifiers 	
Applications	<ul style="list-style-type: none"> • Reference Source for Lock-In Amplifier 	
Block Diagram	<p style="text-align: right; font-size: small;">BS01-1101-12</p>	
Specifications	<p><i>Test Conditions</i></p> <p>Oscillator Frequency</p> <p> Frequency Range</p> <p> Manual Frequency Control</p> <p> Remote Frequency Control</p> <p> THD</p> <p> Temperature Coefficient</p> <p>Oscillator Amplitude</p> <p> Amplitude Range</p> <p> Amplitude Control</p> <p> Amplitude Accuracy</p> <p>Oscillator Output</p> <p> Output Impedance</p> <p> Maximum Output Current</p> <p>External Synchronization</p> <p> Synchronization Input</p> <p> Sync. Input Voltage Level</p> <p> Sync. Input Current</p> <p>Power Supply</p> <p> Supply Voltage</p> <p> Supply Current</p>	<p>$V_s = \pm 5 V, T_a = 25^\circ C$</p> <p>4 ranges, 5 Hz ... 130 kHz total (factory set at 1 kHz)</p> <p>4 range settings via jumpers 5-6 and 7-8, adjustable frequency within range via 25-turn trimpot</p> <p>4 range settings via digital control input pins 4 and 6, leave jumpers 5-6 and 7-8 open, adjustable frequency within range via control voltage 0 V ... + 10 V at pin 10 with reference to GND pin 8</p> <p>0.8 % typ.</p> <p>800 ppm/K allow 20 min warm-up time for good temperature stability</p> <p>0 ... 2 Vrms (factory set at 1 Vrms)</p> <p>25-turn trimpot</p> <p>100 ppm/K</p> <p>10 Ω (terminate with load > 1 kΩ)</p> <p>± 5 mA</p> <p>opto-coupler input with reference to synchronization ground pin 3</p> <p>Low: - 0.8 V ... + 1.2 V, High: + 3.5 V ... + 6 V</p> <p>0 mA @ 0 V, 6 mA @ + 5 V typ.</p> <p>± 5 V</p> <p>± 70 mA</p>

Reference Sine Oscillator Module for LIA-BV-150/LIA-MV-200 Series

Board	Dimensions Weight	31 mm x 39 mm 10 g (0.022 lbs)																																	
Temperature Range	Storage Temperature Operating Temperature	- 40 ... + 100 °C 0 ... + 60 °C																																	
Absolute Maximum Ratings	Power Supply Voltage	± 6 V																																	
Jumper Settings (JP6)	Frequency Range Selection	<table style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 33%;">5 - 6</th> <th style="width: 33%;">7 - 8</th> <th style="width: 33%;">Frequency Range</th> </tr> </thead> <tbody> <tr> <td>close</td> <td>close</td> <td>5 Hz ... 90 Hz</td> </tr> <tr> <td>open</td> <td>close</td> <td>60 Hz ... 1.2 kHz</td> </tr> <tr> <td>close</td> <td>open</td> <td>900 Hz ... 18 kHz</td> </tr> <tr> <td>open</td> <td>open</td> <td>7 kHz ... 130 kHz</td> </tr> </tbody> </table> <table style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 33%;">1 - 2</th> <th style="width: 33%;">Control Mode</th> <th style="width: 33%;"></th> </tr> </thead> <tbody> <tr> <td>open</td> <td>trimpot control</td> <td></td> </tr> <tr> <td>close</td> <td>voltage control (external interface)</td> <td></td> </tr> </tbody> </table> <table style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="width: 33%;">3 - 4</th> <th style="width: 33%;">Synchronization</th> <th style="width: 33%;"></th> </tr> </thead> <tbody> <tr> <td>open</td> <td>on</td> <td></td> </tr> <tr> <td>close</td> <td>off</td> <td></td> </tr> </tbody> </table>	5 - 6	7 - 8	Frequency Range	close	close	5 Hz ... 90 Hz	open	close	60 Hz ... 1.2 kHz	close	open	900 Hz ... 18 kHz	open	open	7 kHz ... 130 kHz	1 - 2	Control Mode		open	trimpot control		close	voltage control (external interface)		3 - 4	Synchronization		open	on		close	off	
5 - 6	7 - 8	Frequency Range																																	
close	close	5 Hz ... 90 Hz																																	
open	close	60 Hz ... 1.2 kHz																																	
close	open	900 Hz ... 18 kHz																																	
open	open	7 kHz ... 130 kHz																																	
1 - 2	Control Mode																																		
open	trimpot control																																		
close	voltage control (external interface)																																		
3 - 4	Synchronization																																		
open	on																																		
close	off																																		
Jumper Positions Diagram																																			
Connector	Connector Type	2 mm pitch socket, 10-pin																																	
	Oscillator Output	Pin 2: oscillator output Pin 8: output GND																																	
	Control Inputs	Pin 4: frequency range control input, MSB Pin 6: frequency range control input, LSB Pin 10: frequency control input Pin 1: external synchronization input Pin 3: external synchronization input GND																																	
	Power Supply	Pin 9: power supply - 5V Pin 5: power supply + 5V Pin 7: power supply GND																																	

FEMTO Messtechnik GmbH
Paul-Lincke-Ufer 34
D-10999 Berlin · Germany
Tel.: +49 (0)30 - 4 46 93 86
Fax: +49 (0)30 - 4 46 93 88
E-Mail: info@femto.de
http://www.femto.de

Specifications are subject to change without notice. Information furnished herein is believed to be accurate and reliable. However, no responsibility is assumed by FEMTO Messtechnik GmbH for its use, nor for any infringement of patents or other rights granted by implication or otherwise under any patent rights of FEMTO Messtechnik GmbH. Product names mentioned may also be trademarks used here for identification purposes only.
© by FEMTO Messtechnik GmbH
Printed in Germany